

HDZ8P Miniature Relay

Function

- Used to implement the conversion of intermediate control signals and low-power output, In the field of industrial control, used in conjunction with contactors, relays, circuit breakers, etc.

Order Information

Rated Current	Poles	LED	Voltage Type	Reference
5A	2	L	AC	HDZ8P052L*1
		None	AC	HDZ8P052*1
		L	DC	HDZ8P052L*Z1
		None	DC	HDZ8P052*Z1
	3	L	AC	HDZ8P053L*1
		None	AC	HDZ8P053*1
		L	DC	HDZ8P053L*Z1
		None	DC	HDZ8P053*Z1
	4	L	AC	HDZ8P054L*1
		None	AC	HDZ8P054*1
		L	DC	HDZ8P054L*Z1
		None	DC	HDZ8P054*Z1
3A	4	L	AC	HDZ8P034L*1
		None	AC	HDZ8P034*1
		L	DC	HDZ8P034L*Z1
		None	DC	HDZ8P034*Z1
10A	2	L	AC	HDZ8P102L*1
		None	AC	HDZ8P102*1
		L	DC	HDZ8P102L*Z1
		None	DC	HDZ8P102*Z1
	3	L	AC	HDZ8P103L*1
		None	AC	HDZ8P103*1
		L	DC	HDZ8P103L*Z1
		None	DC	HDZ8P103*Z1
	4	L	AC	HDZ8P104L*1
		None	AC	HDZ8P104*1
		L	DC	HDZ8P104L*Z1
		None	DC	HDZ8P104*Z1



HDZ8P Miniature Relay

Technical information

	5A		3A,5A	10A		
	2P	3P	4P	2P	3P	4P
Coil voltage	AC6V-380V ,DC6V-220V					
Contact capacity	5A/220VAC 30VDC		3-5A/220VAC 30VDC		10A 250VAC/ 28VDC	
LED	LED ,No LED					
Nominal Coil Power	0.9W/1.2VA		0.9W/1.2VA		1.4W/2VA	1.5W/2.5VA
Contact Resistance	≤100mΩ		≤50mΩ			
Insulation Resistance	≥100mΩ					
Dielectric Strength	BCC 1500VAC 1minute					
	BOC 1000VAC 1minute					
Operate /Release Time	25ms /25ms					
Installation method	PCB installation, Socket			PCB mounting, Socket		